

Datasheet

COCOMM

F360



Terminal requirements HW

Display	LCD 2.4" (monochrome) Resolution: 128*64
Main system	Chipset: Unisoc T107 OS: MOCOR-DROID
Memory	RAM 48 MB, ROM 128 MB
Connectors	SIM holder Memory Holder USB-C (data connector and charging) Power supply connector Jack 3.5 CTIA format Screw slot for battery cover All wires connect with connectors

Internal battery	BL-5C type (1050mA)
Internal microphone	Microphone hand free
Networks bands	LTE: 1/3/7/8/20/28/38 WCDMA: B1/B8 GSM: 900/1800
Antennas	GSM/WCDMA/UMTS – External antenna Sticker type Bluetooth 5
Physical specs	Keypad Stand base
Keypad	Alphanumeric keypad At least 2 memory buttons Answer/reject buttons Softkeys (at least 2) Directional button OK button Hold, Transfer, Conference buttons Cancel button Recall button Mute button (Include LED) Volumen UP/DOWN buttons Handfree button
Common apps	Dialer Contacts (phonebook) History call Settings Calendar FM Radio SMS Sim tool kit Clock – Alarm Calculator Bluetooth Audio profiles

Features

Full voLTE & HDVoice
Long pressing dialing(speedkeys)
Phonebook phone storage - 2000 contacts
Custom Wallpapers (not support)
Built in melody ringtones
Time-clock option in display
Languages (Spanish, French, Portuguese, English (United Kingdom), Catalan, Euskara, Galician, Italian)
Conversation time: 8 hours
GSM FR_AMR-WB support
GEA2 and GEA3
A5/4 algorithm supported(not support)
EVS codec (voLTE) supported

Advance features

FOTA
AoCC (advice of charge) (beep sound when power supply is connected or disconnected)
Multiconference and three-way calling
Explicit Call Transfer through keys and menu
USB: FW updated and catch log
